


Ericsson R320s WAP settings

1. From the idle mode press left soft button twice to enter the **WAP Services** menu.
2. Use  until **WAP Settings** is displayed and press YES button.
3. Choose vacant Profile by pressing YES button.
4. A list of configuration parameters will be displayed. You should fill the appropriate data in and press YES button each time at the end of input:

Rename – **Azercell**

Edit Homepage:

Title – **Azercell**

Address – **wap.azercell.com**

Show Images – **On**

Access:

Access Type – **GSM Data**

Response Timer – **150** sec

Service Center – **75767575111**

GSM Data:

Phone Number – **75767575111**

Dial Type – **ISDN**

User ID – **wapuser**

Password – **wap2000**

Inactive Timeout – **300** sec

Press NO button to return to the previous menu.

Gateway:



User ID – **wapuser**

Password – **wap2000**

Data Address – **062.217.128.038**

SMS Address – *leave empty*

*Press NO button 4 times to return to the **WAP Services** menu.*

5. If you did not have any other WAP profile then this one entered will be activated by default. In case you have some other profile activated earlier on your phone then use  until **WAP Profile** is highlighted and press YES button. Select AZERCELL profile and press YES button.
6. In order to activate the WAP browser from the idle mode of your phone press the left soft button twice, use  until **AZERCELL** is highlighted and press YES button. In order to quit the browsing press and hold NO button.

Thank you for using **WAPCELL !!**