

Ericsson T39m WAP settings

1. From the idle mode press the left soft button twice and then YES button to enter the **WAP Services** menu.
2. Press the right soft button until **WAP Settings** is displayed and press YES button.
3. Choose vacant **Profile** by pressing YES button.
4. A list of configuration parameters will be displayed. You should fill the appropriate data in and press YES button each time at the end of input:

Rename – **AZERCELL**

Chg homepage:

Title – **Azercell WAP**

Address – **http://wap.azercell.com**

Save to – **Current profile**

Gateway:

IP settings => Connect using => Add account? – **GSM Data**

Name – **Azercell**

Phone no: – **7575111**

User id: – **wapuser**

Password: – **wap2000**

Save? – *press YES*

Add account? – **Azercell**

IP address – 062.217.128.038

User id – **wapuser**

Password – **wap2000**

Data mode – **Connection less**

Security – **Off**

Show images – **On**

Response timer – **300** sec

*Press NO button 4 times to return to the **WAP Services** menu.*

5. If you did not have any other WAP profile then this one entered will be activated by default. In case you have some other profile activated earlier on your phone then press the left soft button until **Select Profile** is highlighted and press YES button. Select **AZERCELL** profile and press YES button.
6. In order to activate the WAP browser from the idle mode of your phone, press the left soft button twice and then press YES button twice in succession. In order to quit the browsing press and hold NO button.

Thank you for using **WAPCELL !!**