

## **Samsung SGH-N200 WAP settings**

1. Press the left soft button to enter the Menu.
2. Press the scroller up till "**Settings**" and press "**Select**" with the left soft button.
3. Press the scroller up until "**Browser Settings**" is highlighted. Then press "**Select**" with the left soft button. Press "**OK**". Choose the vacant **Proxy** and press "**Select**" with the left soft button.
4. You will see the number of settings which should be entered as follows:  
Proxy Name - **Azercell**  
WDP address – **062.217.128.038**  
Port number – **9201**  
Home URL – **http://wap.azercell.com**  
Access Point: (*press Edit*)  
    NAS Phone Number – **75767575111**  
    Login Name – **wapuser**  
    Password – **wap2000**  
    Network Type – **V.110 Nontrans**
5. Press the right soft button three times to return to **Proxy Settings** menu and press the scroller down until **Current Proxy** is highlighted. Then press **OK** with the left soft button. Choose **Azercell** profile(proxy) and press "**Select**" with the left soft button.
6. Press the right soft button once to return to **Settings** menu. Then press the scroller down till **Phone Settings** and press "**Select**" with the left soft button.
7. Press the scroller down till **Own Number** and press "**Select**" with the left soft button. Press **Options**, then choose **Add** and press **OK** with the left soft button.
8. Type **Azercell** and press **OK**. Type **75767575111** and press **Save** with the left soft button. Press **NO** button to return to stand-by mode.
9. In order to activate WAP browser press **i/C** button. *Tip: use this button as Back button when browsing WAP pages.*
10. In order to quit WAP press **NO** button.

Thank you for using **WAPCELL !!**