

Sony CMD-J5 WAP settings

1. Press the Jog Dial in to enter the Menu.
2. Rotate the Jog Dial until “**WAP**” is displayed on the screen. Then press the Jog Dial in.
3. Rotate the Jog Dial until “**Settings**” is highlighted. Then press the Jog Dial in three times.
4. “**Security Code**” will be displayed on the screen. Enter **0000** and press the Jog Dial in.
5. You will have the number of settings which should be entered as follows:
Name – **Azercell**
Home Page – **http://wap.azercell.com**
Server Type – **WAP**
Bearer Service – **Data**
Provider:
 - Dial-up number – **7575111**
 - ISP User Name – **wapuser**
 - ISP password – **wap2000**
 - Data Call Type - **Analogue**
 - GW Server – **62.217.128.38** (remember do not enter first zero’s in IP groups)
 - Security – **off**
6. There will be 3 more settings left (**Service Center, Proxy and Details**). Do not enter anything for them and keep rotating the Jog Dial until “<.....” is highlighted. Then press the Jog Dial in. Rotate the Jog Dial until “**Set Home**” is highlighted and press the Jog Dial in.
7. Press the Jog Dial in and hold it until you are in standby mode.
8. In order to WAP press the Centre Key in standby mode and go for Home.

Thank you for using **WAPCELL !!**