

## **Sony CMD-Z7 WAP settings**

1. Press the Jog Dial towards the back to enter the **Applications** menu.
2. Rotate the Jog Dial until "**WAP**" is highlighted. Then press the Jog Dial in.
3. Rotate the Jog Dial until "**Settings**" is highlighted. Then press the Jog Dial in.
4. Rotate the Jog Dial until "**Empty**" profile is highlighted. Then press the Jog Dial in.
5. Press "**Edit**" with the Jog Dial.
6. "**Security Code**" will be displayed on the screen. Enter **0000** and press the Jog Dial in.
7. You will see the number of settings which should be entered as follows:
  - Name – **Azercell**
  - Home Page – **http://wap.azercell.com**
  - Server Type – **WAP**
  - Bearer Service – **Data**
  - Provider:
    - Dial-Up Number – **7575111**
    - ISP User Name – **wapuser**
    - ISP Password – **wap2000**
    - Data call type - **Analogue**
    - GW Server – **62.217.128.38**
    - Security – **off**
8. There will be 3 more settings left (**Service Centre, Proxy** and **Details**). Do not enter anything for them. Press the Jog Dial towards the front then rotate it until "**Set home**" is highlighted and press it in. Then again press the Jog Dial towards the front and rotate it until "**Home**" is highlighted. Press the Jog Dial in to activate the browser.
9. In order to quit WAP press NO button.

Thank you for using **WAPCELL !!**